

Specifikacija

50m kotur





Kod proizvoda	Snaga	Tc(K) Temperatura boje svetlosti	(lm) Lumeni	LED tip	Broj čipova po metru	Dužina kotura	IPxx	Ugao rasipanja svetlosti	L W H Dimenzija (mm)	
MLC-2835H60	4.8W/1m	3000K	1200 Lm/1m	SMD LED 2835	60 kom. / 1m	50m	IP65	120°	50.000 10 10	A ⁺
MLC-2835H60	4.8W/1m	6500K	1200 Lm/1m	SMD LED 2835	60 kom. / 1m	50m	IP65	120°	50.000 10 10	A ⁺
MLC-2835H120	6W/1m	3000K	2400 Lm/1m	SMD LED 2835	120 kom. / 1m	50m	IP65	120°	50.000 10 10	A ⁺
MLC-2835H120	6W/1m	6500K	2400 Lm/1m	SMD LED 2835	120 kom. / 1m	50m	IP65	120°	50.000 10 10	A ⁺

*Najmanja dužina za sečenje LED trake 220V je 1m. LED traka 220V može raditi u jednoj celini na dužini od 50m.
U kompletu: Konektor, 10 obujmica, 2 nastavka i 2 završetka.



Upozorenje:

- Pre instalacije pažljivo pročitati uputstvo i sačuvati ga.
- Instalaciju treba da izvrši kvalifikovani električar.
- Pre instaliranja isključiti dovod struje.
- Pažljivo odabrati mesto postavljanja LED trake kako ne bi došlo do oštećenja.
- LED traku seći samo nakon svakih jedan (1) metar, odnosno na mestima gde je obeleženo za to. Ukoliko se LED traka pogrešno iseče, oštećeni deo ne možete koristiti, treba ga odmah baciti.
- Mesto postavljanja LED trake treba biti **čisto i suvo**.
- LED trake sa ne smeju se premazivati farbom ili sličnim sredstvima, u suprotnom može uticati na produkciju svetlosti.
- Instalirati zaštitnu kapicu na kraju.




Montaža:

Izmeriti položaj i razmak postavljanja trake pre sečenja.
Odstraniti zaštitnu plastičnu traku i zalepiti na željeno mesto.
Uključiti struju.



Ova svetiljka sadrži ugrađene LED sijalice.




LED

Sijalice u svetiljci se ne mogu zameniti.



874/2012



PROTECTION FROM BURNS AND FIRE

Do not operate the LED strip if the ambient temperature (Ta) exceeds 45° C (113° C). Do not modify the LED strip in any way not described in this manual or instal than genuine Mitea Lighting parts. Use only accessories approved by Mitea Lighting. If any of the product temperature readouts exceed the level, provide fan assistance to give active cooling to the installation.